

Change Communications Method in Verifone VX520

Integrated Payments no longer supports dial-up communications, please follow the below instructions to change the communications method in the terminal from dial mode to CommServer (Ethernet).

Please note that the terminal must be connected to an ethernet cable and connected to the internet going forward.

- **Press the [6] key to access the Quick Setup Options.**
- **If the terminal prompts for a password during this process, the password is 1 Alpha Alpha 66831**

Display			Action
Quick Setup		Phone Terminal Communications	Select F4 [Communications]
Communications	View Print	F2 F3	To print parameters, press [F3] To edit/view parameters press [F2]
VNTV Auth Comm {Dial or CommServer}	Prev Next Edit Exit	F1 F2 F3 F4	Primary communication type for authorizations CommServer = Ethernet
VNTV Bankup Auto Backup	Prev Next Edit Exit	F1 F2 F3 F4	<ul style="list-style-type: none"> None, Auto Backup, Prompt Backup, Switch Backup, Use Backup. Auto Backup will switch to dial automatically if Ethernet fails due to no connection.
VNTV Settle Comm {Dial or CommServer}	Prev Next Edit Exit	F1 F2 F3 F4	Primary communication type for Settlements CommServer = Ethernet
DL Modem Dial	Prev Next Edit Exit	F1 F2 F3 F4	Download Modem Type. Dial or Other. Not Used.