
















S80 Standard Dial Download

	<p>This is the screen the terminal will generate, after booting up. Press the Menu Key </p> <ul style="list-style-type: none">• This should bring you to the Main Menu
	<p>From the Main Menu – Select Communication Settings</p> <ul style="list-style-type: none">• This will take you to the Comm. Options menu
	<p>From the Comm Options Menu – Select Backup Comm.</p>

 <p>A screenshot of a terminal screen showing a menu titled "Backup Comm. :2". The menu items are "1.LAN", "2.Dial", and "3.None". The "3.None" option is highlighted with a dark bar.</p>	<ul style="list-style-type: none">• Press the Arrow down key until None is highlighted and press enter or press 3<ul style="list-style-type: none">○ This will bring you back to the Comm. Options Menu
 <p>A screenshot of a terminal screen showing a menu titled "COMM. OPTIONS:". The menu items are "1.Main Communication", "2.Backup Comm.", "3.LAN Parameters", "4.Dial Parameters", and "5.Maximum Tries". The "2.Backup Comm." option is highlighted with a dark bar.</p>	<p>Select "Main Communications" by highlighting and pressing enter or press 1</p>
 <p>A screenshot of a terminal screen showing a menu titled "Main Comm. :1". The menu items are "1.LAN" and "2.Dial". The "2.Dial" option is highlighted with a dark bar.</p>	<p>Arrow down to highlight Dial and press enter or press 2</p> <ul style="list-style-type: none">• This will bring you back to the Comm. Options menu
 <p>A screenshot of a terminal screen showing a menu titled "COMM. OPTIONS:". The menu items are "1.Main Communication", "2.Backup Comm.", "3.LAN Parameters", "4.Dial Parameters", and "5.Maximum Tries". The "2.Backup Comm." option is highlighted with a dark bar.</p>	<ul style="list-style-type: none">• Press the Red Cancel key 1 time, and you'll be back to the Main Menu Screen

	<ul style="list-style-type: none">• Select System Settings by pressing the green enter key or press 1
	<p>Select App Management</p>
	<p>The Password should be the current date (ddmmyyyy) – in the end it'll be the date that is reflected on the terminal</p> <ul style="list-style-type: none">• If the date/time are wrong on the terminal- then the pw will be the date that displays on the terminal screen
	<ul style="list-style-type: none">• Select Activate

	<p>Select Online by pressing the Green Enter key or press 1</p>
	<p>1 of 2 things can happen</p> <ol style="list-style-type: none">1. If the terminal already has a Terminal ID stored, the terminal will connect with the PaxStore to Activate.2. If the terminal doesn't have a Terminal ID stored, the display will ask you to enter the Terminal ID.<ol style="list-style-type: none">a. Enter the tid with the prefix of 00000022<ol style="list-style-type: none">i. Example 00000022 + TIDb. Once this is done – the App Load Menu will populate
	<p>Select App Update</p> <ul style="list-style-type: none">• The terminal should start downloading the file• If the device reads no download?<ul style="list-style-type: none">○ Reboot the terminal and allow Health Check to start the download