



















hWP VX520 Download instructions - Ethernet

Step	Terminal Response	Action
1		Press F2 and F4 together.
2	TERMINAL MGR ENTRY Please Enter Password ----- Press CANCEL to exit	Key the system password ("1" [ALPHA] [ALPHA] "66831") and press  .
3	VERIX TERMINAL MGR 1) Edit Parameters 2) Download 3) Restart ↓ ↑	Select "Download."
4	VERIX TERMINAL MGR Group ID: _1	Press  .
5	VERIX TERMINAL MGR Please enter Password for <i>GID</i> 1 -----	Key the GID password ("23378463") and press  .
6	VTM DOWNLOAD MGR G1 1) Single-app 2) Multi-app ↓ ↑	Select "Multi-app."
7	VTM DOWNLOAD MGR G1 1) Full dnld 2) Partial dnld ↓ ↑	Select "Full dnld."
8	VTM DOWNLOAD MGR G1 GIDS to ERASE: 1) CHANGE CHOICES 2) CONTINUE	Press [1] (Change Choices)
9	VTM DOWNLOAD MGR G1 CLEAR APPLICATION FROM GROUP 1? 1) YES 2) NO	Press [1] (Yes)
10	VTM DOWNLOAD MGR G1 **** WARNING **** CONFIRM DELETION FOR APPLICATION 1) YES 2) NO	Press [1] (Yes)


hWP VX520 Download instructions - Ethernet

11	VTM DOWNLOAD MGR G1 CLEAR APPLICATION FROM GROUP 2? 1) YES 2) NO	Press [1] (Yes)
12	VTM DOWNLOAD MGR G1 **** WARNING **** CONFIRM DELETION FOR APPLICATION 1) YES 2) NO	Press [1] (Yes)
13	VTM DOWNLOAD MGR G1 1) Modem 2) COM1 3) COM7 <div style="display: flex; justify-content: space-around; align-items: center;"> ↓ ↓ ↑ </div>	Press  until the terminal displays "TCPIP."
14	VTM DOWNLOAD MGR G1 1> SD Card 2) USB Flash Memory 3) TCPIP <div style="display: flex; justify-content: space-around; align-items: center;"> ↓ ↓ ↑ </div>	Select "TCPIP."
15	<div style="background-color: black; color: white; padding: 5px; text-align: center;">Please select Download</div> <div style="text-align: center;">FTP</div> <div style="display: flex; justify-content: space-around; align-items: center;"> ↓ ↑ </div>	Press  .
16	<div style="background-color: black; color: white; padding: 5px; text-align: center;">Comm Technology Default Interface</div> <div style="text-align: center;">Ethernet PPP/Dial</div> <div style="display: flex; justify-content: space-around; align-items: center;"> ↓ ↑ </div>	Press  .
17	<div style="background-color: black; color: white; padding: 5px; text-align: center;">Download Download</div> <div style="text-align: center;">Setup Timeouts Setup Network</div> <div style="display: flex; justify-content: space-around; align-items: center;"> ↓ ↑ </div>	Press  .

hWP VX520 Download instructions - Ethernet

18	<p>Download URL String IP Address</p>	Press  .
19	<p>Download URL/address VERILOAD.LYNKSYSTEMS. COM</p> <p style="text-align: right;">Edit</p>	<p>Verify that the terminal displays "VERILOAD.LYNKSYSTEMS.COM" and press .</p> <p>or</p> <p>REPORTS</p> <p>Press  to edit.</p>
20	<p>Download Port 8013</p> <p style="text-align: right;">Edit</p>	<p>Verify that the terminal displays "8013" and press .</p> <p>or</p> <p>REPORTS</p> <p>Press  to edit.</p>
21	<p>Download SSL False</p> <p style="text-align: right;">Edit</p>	<p>Verify that the terminal displays "SSL False" and press .</p> <p>or</p> <p>REPORTS</p> <p>Press  to edit.</p>
22	<p>Download Terminal ID XXXXXX</p> <p style="text-align: right;">Edit</p>	<p>Verify that the terminal displays the correct TID and press . <i>This will be the "LK" number on the terminal sticker. Use only the numbers following "LK".</i></p> <p>or</p> <p>REPORTS</p> <p>Press  to edit.</p>
23	<p>Download Application Name *MA</p> <p style="text-align: right;">Edit</p>	<p>Verify that the terminal displays "*MA" and press .</p> <p>or</p> <p>REPORTS</p> <p>Press  to edit.</p>

hWP VX520 Download instructions - Ethernet

24	Download Group ID Full VERILOAD.LYNKSYSTEMS.COM Port:8013 SSL: Disabled ↓ Print	Verify that the terminal displays the correct download information. Then scroll to the next screen.
25	Download Terminal ID *ZT= XXXXXX Application Name *ZA= *MA ↑ Print	Verify that the terminal displays the correct download information and press  .
26	VTM DOWNLOAD MGR G1 App ID: *MA Status: Downloading *_____	The terminal displays dashes that turn into asterisks as the download completes. The terminal restarts and displays the idle prompt.