

Ingenico ICT220 Download Instructions - IP

CONFIDENTIAL




ATTENTION! Before You Get Started

1. Make sure that you have ample time to perform this download. You will not be able to process transactions on the terminal once the download process begins.
2. Settle any open transactions. Terminal downloads will delete any open batches and the transactions within.
3. Have your newly provided terminal identification number (TID) handy. You will need it to complete the download
4. ***Can you download over an internet connection (IP)?*** These files are very large and the recommended download method is over IP.
5. Voice over IP (VOIP) Connections - You should avoid attempting dial downloads over VOIP lines. Dial downloads were designed to be conducted over analog telephone lines.

Helpful Hints:

- Most of the buttons to be pressed will be circled in red.
- Your screen should match the screen on the instructions (besides your unique Terminal ID Number).




Step 1

To perform the EMV application download

Press [F] key from home screen

*****Please ensure your batch is settled before you attempt any downloads.*****



Step 2


Enter Admin Password

V123456 or
P123456

Press the number key with
the letter and then press
[F] key to change to letters


Example V = 8, [F], [F], [F]

Press the [GREEN] key
when complete




Step 3

Select TADU



Step 4

Scroll down and select
3 - DELETE SW




Step 5

Type in 246135
Press [Enter]



Step 6

Press [Enter] to select
0 - Remove Apps




Step 7

Terminal will display warning.
Press [F1] key for YES




Step 8

The terminal will restart.




Step 9

The terminal will return to the TADU idle prompt. Press the [F] key.




Step 10

Select TADU and press the [GREEN] key




Step 11

Press [0] for CONFIGURE




Step 12

Press [0] for Full



Step 13

Press [1] for Ethernet



Step 14

Press [0] for Dynamic



Step 15

Verify address is correct.
It should be
TDV1.FTPSLLC.COM

If you need to change it
press the [YELLOW] key
and then create letters by
pressing the
corresponding number key
followed by the [F] key
until the correct letter
appears.

Example: T = 8, [F]

Press the [GREEN] key
when complete




Step 16

Verify the port is correct.
It should be 8013.

If you need to update this
press the [YELLOW] key
and then key in 8013.

Press the [GREEN] key
when complete



Step 17

Select [1] for OFF



Step 18

Confirm the model states ICT220 and press the [GREEN] key

If not press the [YELLOW] key to clear. Enter ICT220

To create letters you will press the corresponding number and then the [F] key until the correct letter appears

Example: I = 4, [F], [F], [F]

Press the [GREEN] key



Step 19

Press the [YELLOW] key to clear the Application Name

Enter the specific application name provided in the email from Vantiv. (Example: HRTS220VC)

To create letters you will press the corresponding number and then the [F] key until the correct letter appears

Example: H = 4, [F], [F]

Press the [GREEN] key when finished




Step 20

Press the [YELLOW] key to clear the Terminal ID.


Type in the Terminal ID provided in the email from Vantiv.

Press the [GREEN] key when finished



Step 21

Press [1] for DOWNLOAD



Step 22

The download will begin. Estimated time for download varies but is typically between 7-10 minutes.

vantiv®