








## hWP VX520 Download instructions - Dial

Step	Terminal Response	Action
1		Press <b>F2</b> and <b>F4</b> together.
2	TERMINAL MGR ENTRY Please Enter Password ----- Press CANCEL to exit	Key the system password ("1" [ALPHA] [ALPHA] "66831") and press  .
3	VERIX TERMINAL MGR 1) Edit Parameters <b>2) Download</b> 3) Restart  ↓ ↑	Select "Download."
4	VERIX TERMINAL MGR Group ID: _1	Press  .
5	VERIX TERMINAL MGR Please enter Password for GID 1 -----	Key the GID password ("23378463") and press  .
6	VTM DOWNLOAD MGR G1 1) Single-app <b>2) Multi-app</b>  ↓ ↑	Select "Multi-app."
7	VTM DOWNLOAD MGR G1 <b>1) Full dnld</b> 2) Partial dnld  ↓ ↑	Select "Full dnld."
8	VTM DOWNLOAD MGR G1 GIDS to ERASE: <b>1) CHANGE CHOICES</b> 2) CONTINUE	Press [1] (Change Choices)
9	VTM DOWNLOAD MGR G1 CLEAR APPLICATION FROM GROUP 1? <b>1) YES</b> 2) NO	Press [1] (Yes)
10	VTM DOWNLOAD MGR G1 **** WARNING **** CONFIRM DELETION FOR APPLICATION <b>1) YES</b> 2) NO	Press [1] (Yes)

## hWP VX520 Download instructions - Dial

11	VTM DOWNLOAD MGR G1 CLEAR APPLICATION FROM GROUP 2? 1) YES 2) NO	Press [1] (Yes)
12	VTM DOWNLOAD MGR G1 **** WARNING **** CONFIRM DELETION FOR APPLICATION 1) YES 2) NO	Press [1] (Yes)
13	VTM DOWNLOAD MGR G1 1) Modem 2) COM1 3) COM7 ↓ ↑	Select "Modem."
14	VTM DOWNLOAD MGR G1 *ZA= *MA *ZP= 18009495965 *ZT= XXXXXX *ZB= 1000 1) Edit 2) Start ↓ ↑	<i>(If the parameters are correct)</i> Select "Start" and skip to step 8.  <i>or</i> <i>(If the parameters are not correct)</i> Select "Edit" and continue with the next step.
15	VTM DOWNLOAD MGR G1 1) Single-app 2) Multi-app ↓ ↑	Select "Multi-app."
16	VTM DOWNLOAD MGR G1 *ZP Host Phone num 18009495965----- -----	Verify that the terminal displays 18009495965 and press  .  REPORTS Press  to edit.
17	VTM DOWNLOAD MGR G1 *ZT Terminal ID XXXXXX-----	Verify the terminal displays the correct TID and press  . <i>This will be the "LK" number on the terminal sticker. Use only the number following "LK".</i>  REPORTS Press  to edit.
18	VTM DOWNLOAD MGR G1  Select Block Size	Select "1000."

## hWP VX520 Download instructions - Dial

	<p>For Download</p> <p>1) 1000</p> <p>2) 500</p> <p>3) 240</p> <p style="text-align: right;">↓ ↑</p>	
19	<p>VTM DOWNLOAD MGR G1</p> <p>*ZA= *MA</p> <p>*ZP= 18009495965</p> <p>*ZT= XXXXXX</p> <p>*ZB= 1000</p> <p>1) Edit</p> <p>2) Download</p> <p>3) Restart</p> <p style="text-align: right;">↓ ↑</p>	<p>Press 2 to select "Download".</p>
20	<p>VTM DOWNLOAD MGR G1</p> <p>App ID: *MA</p> <p>Status: Downloading</p> <p>*-----</p>	<p>The terminal displays dashes that turn into asterisks as the download completes. The terminal restarts and displays the idle prompt.</p> <p><b>Note:</b> Each asterisk represents 10% of the download completing.</p>